



# PacketMAX<sup>TM</sup>: 40G Advanced Aggregator

10G/40G/100G | 1U Chassis | 24 Port | Filtering, Aggregating and Load Balancing



The PacketMAX™: 40G Advanced Aggregator is a purpose built network aggregator, designed for use in top-of-rack applications or at the network edge. The system can be used to optimize port utilization of existing infrastructure, or as a stand alone device in L2-L4 Filtering applications.

There are no additional per-port license fees, and it is compatible with MSA compliant QSFP/ QSFP28 pluggables/transceivers. Flexible port speeds (port splitting) can scale according to network needs (10G/40G/100G) and can be changed within the interface menu.

### **Key Features** •

- · Aggregate network traffic to a single or multiple tools (1:1, 1:N, N:1, N:N)
- Supports 10G/40G/100G network speeds
- IPv4 and UDF Filter support
- · Timestamping Layer 2 Header
- 24 fully supported ports no additional per-port license fees
- Port splitting functionality
- Supports jumbo frames
- · 4,000 filter rules

- · Session/flow aware load balancing
- · Hash-based load balancing and Round-Robin distribution
- Forward latency, less than 1uscc
- Hot swappable, dual Power Supplies, AC standard, DC available
- · Management through CLI, GUI, and SNMP
- · RADIUS and TACACS remote user authentication
- sFlow Support

#### FILTERS:

- · User defined filters for Layer 2, 3, and 4
- IPv4, MAC, L4Port, VLAN, Ethertype, IP protocol
- Supports VXLAN decapsulation/encapsulation
- · Supports VLAN Strippping, QinQ support
- Full line rate filtering
- Packet modification

### **APPLICATIONS:**

- ▶ Aggregation of multiple TAP/SPAN ports for increased utilization
- Connect to Network Packet Broker or directly to tools
- > High Density filtering, aggregation and load balancing
- > Aggregation solution for large and medium size data centers
- Aggregation for enterprise and service provider networks

### CompetitiveEdge 🔘



- Purpose built aggregation device
- Full L2-L4 filter support
- · High density system, up to 96x10G ports
- Cisco BiDi support
- VLAN tagging and stripping



### **Have Questions?**



sales@garlandtechnology.com +716.242.8500 garlandtechnology.com

## PacketMAX™: 40G Advanced Aggregator

### 10G/40G/100G | 1U Chassis | 24 Port | Filtering, Aggregating and Load Balancing

Advanced Aggregator options						
Model #	Ports	Network Speed	40G Port	100G Port	Power Supplies	
AA40G24AC		10/40/100G	(20) QSFP+	(4) QSFP28	AC	
AA40G24DC		10/40/100G	(20) QSFP+	(4) QSFP28	DC	

Available Pluggables & Cables:		
Model #	Description	
QSFP+40GBiDi	QSFP+ 40Gigabit-SR-BiDi Multi-Mode Fiber LC Connector	
QSFP+40G	QSFP+ 40Gigabit-SR Multi-Mode Fiber MPO-12 Connector	
QSFP+40-LR4	QSFP+ 40Gigabit-LR4 Single Mode Fiber LC Connector	
QSFP28-4SFP28-Cable_1	100 Gigabit Ethernet QSFP28 to (4) x 25 Gigabit Ethernet SFP28 Splitter Cable, 1 Meter	

#### **1U Chassis Specifications:**

Support for: QSFP+, QSFP28, SFP+ (SR, LR, ER) Operating Temp.: 0C to 50C / 32F to 122F Operating Humidity: 20% to 70% non-condensing

Airflow: front to back


Voltage: AC: 100v - 240v 50/60Hz

#### AA40G24AC Dimensions:

1.75"H x 17.3"W x 18.5"D (44.45 mm H x 439.42mm W x 469.9mm D)

### **Port Configuration**

### Each port can be individually configured for optimum flexibility





This document is for informational purposes only. The information in this document, believed by Garland Technology to be accurate as of the date of publication, is subject to change without notice. Garland Technology assumes no responsibility for any errors or omissions in this document and shall have no obligation to you as a result of having made this document available to you or based upon the information it contains. ©2019 Garland Technology LLC. All Rights Reserved